


460-XXX-SP SERIES

Single-phase voltage monitor





Wiring Diagram



Description

The 460-100-SP is used on 95-120VAC, 50*/60Hz single-phase motors and the 460-200-SP is used on 190-240VAC, 50*/60Hz single-phase motors to protect them from damaging high and low voltage conditions. An adjustment knob allows the user to set a 1-500 second restart delay. The variable restart delay is also a power-up delay and can be utilized to stagger-start motors on the same system.

A unique microcontroller-based, voltage-sensing circuit constantly monitors the voltage to detect harmful power line conditions. When a harmful condition is detected, the MotorSaver's output relay is deactivated after a specified trip delay. The output relay reactivates after power line conditions return to an acceptable level and a specified amount of time has elapsed (restart delay). The trip delay prevents nuisance tripping due to rapidly fluctuating power line conditions.

Features & Benefits

FEATURES	BENEFITS	
Proprietary microcontroller based circuitry	Constant monitoring of voltage to detect harmful power line conditions, even before a motor starts	
Fixed trip delay 4s	Prevents nuisance tripping due to rapidly fluctuating power line conditions	
Adjustable restart delay (1-500s)	Allows staggered start up of multiple motors on the same system to prevent a low voltage condition	
Advanced LED indication	Provides diagnostics which can be used for troubleshooting and to determine relay status	
DIN rail or surface mountable		

Ordering Information

MODEL	LINE VOTAGE
460-100-SP	95-120VAC
460-200-SP	190-240VAC



460-XXX-SP SERIES

Specifications

Input Characteristics

Line Voltage 460-100-SP 95-120VAC 460-200-SP 190-240VAC Frequency 50*/60Hz

Functional Characteristics Low Voltage (% of setpoint):

High Voltage (% of setpoint)

Trip Delay Time

Low or High Voltage 4 seconds fixed

Restart Delay Time

After a Fault 1-500 seconds adjustable
After a Complete Power Loss 1-500 seconds adjustable

Output Characteristics
Output Contact Rating

(1 Form C)

 Pilot Duty
 480VA @ 240VAC, B300

 General Purpose
 10A @ 240VAC

General Characteristics

Ambient Temperature Range

 Operating
 -40° to 70°C (-40° to 158°F)

 Storage
 -40° to 80°C (-40° to 176°F)

Maximum Input Power 6 W

Class of Protection IP20, NEMA 1 (finger safe)

Relative Humidity 10-95%, non-condensing per IEC 68-2-3

Terminal Torque 4.5 in.-lbs

Wire Type Stranded or solid 12-20 AWG, one per terminal

Standards Passed

Electrostatic Discharge (ESD) IEC 61000-4-2, Level 3, 6kV contact, 8kV air

Radio Frequency Immunity,

Radiated 150 MHz, 10V/m

Fast Transient Burst IEC 61000-4-4, Level 3, 3.5 kV input power

and controls

Surge

IEC 61000-4-5, Level 3, 4kV line-to-line;

Level 4, 4kV line-to-ground

ANSI/IEEE C62.41 Surge and Ring Wave Compliance to a

level of 6kV line-to-line

Hi-potential Test Meets UL508 (2 x rated V +1000V for 1 min)

Safety Marks

 UL
 UL508 (File #E68520)

 CE
 IEC 60947-6-2

 Enclosure
 Polycarbonate

Dimensions H 88.9 mm (3.5"); **W** 52.93 mm (2.084");

D 59.69 mm (2.35")

Weight 0.9 lb. (14.4 oz., 408.23 g)

Mounting Method 35mm DIN rail or Surface Mount

(#6 or #8 screws)

*Note: 50 Hz will increase all delay timers by 20%